

Data Sheet

RoamAlert® Pendant Tag

The Pendant Tag is a radio frequency tag that enables staff to automatically bypass exits protected by the RoamAlert wander prevention system.

In facilities with RoamAlert receivers (part no. 804A1301) installed, the Pendant:

- allows individuals (either staff or residents) to call for assistance from anywhere within the system’s coverage area. The same Pendant can be used by staff for both bypass and emergency call.
- can be used as a real time device for locating individuals.



Pendant Tag Specifications	
Part Number	AR3TA01-00D
Model	Pendant Tag
Input Frequency	307 kHz
Output Frequency	433.92 MHz
LED	Distress alarm activity
Operating Temperature	14° to 122°F (-10° to 50° C)
Storage Temperature	-4° to 131°F (-20° to 55° C)
Dimensions	2.24 x 1.37 x 0.40" (5.7 x 3.5 x 1.0 cm)
Weight	0.6 oz. (17 g)
Power Supply	3 V Battery (included)

Product Highlights

- Enables automatic bypass of doors by staff
- Individuals can call for assistance from anywhere within the coverage area when receivers are installed
- LED feedback tells user that the “Distress” message is being transmitted
- Recessed Distress button is easily pressed while avoiding false triggers
- Rugged, attractive case
- Unique serial number identifies each tag
- Automatic low-battery warning in the system software